



# MUSTANG COMMUNICATIONS LTD

EASTFIELD INDUSTRIAL ESTATE, SCARBOROUGH, ENGLAND YO11 3UT

Telephone +44 (0) 1723 582555, FAX +44 (0) 1723 581673

Web: [www.mustang.co.uk](http://www.mustang.co.uk)

email: [service@mustang.co.uk](mailto:service@mustang.co.uk)

[DM5] pm6 issue 7

## DM/5 DESK MICROPHONE: Specifications and Connections

The DM/5 desk microphone is a five zone paging unit featuring high quality capsule, swan neck, and base assembly with captive cable. A momentary operation "press-to-talk" key is fitted together with five zone selection and one 'all-call' toggle switches which may be used to operate priority switching circuits in associated amplifiers or zone control units. The microphone signal is muted prior to operating the PTT switch.

### ELECTRICAL SPECIFICATION

Impedance	200 ohms
Sensitivity	-60 dB rel. 1V/Pa
Frequency response	150Hz - 15kHz
Polar response	Cardioid
Switch current capability	1 Amp DC 24v
Busy Light	Red LED 24v DC 10mA via internal 2k2 resistor

### MECHANICAL SPECIFICATION

Case size	118mm x 160mm x 60mm
Maximum height of assembly	330mm
Cable length	1.8m
Weight	525gm
Microphone	Black, non reflective. Grey cable.
Base	Two part steel. Two-one grey textured paint. Non-skid feet fitted

### CONNECTIONS

#### 4 core Screened

Red - Blue	Microphone audio, balanced floating, normally muted.
Yellow - Clear	Independent switching pair (normally open)
Braid	Screen Signal OV to LPA.1 option if fitted

#### 12 core Screened

Pink	+24v to LPA.1 pre-amp, & busy LED via internal 2k2
Turquoise	0v to Busy LED
Black	Switching 0v
Blue	All Call
Brown	Zone 1
Red	Zone 2
Orange	Zone 3
Yellow	Zone 4
Green	Zone 5
Violet	n/c
Grey	n/c
White	n/c
Braid	Chassis earth.

### LPA.1 PRE-AMPLIFIER OPTION - where fitted

Output	-20dB to 0dB nominal into 600 ohm load, balanced
Maximum signal output	6V RMS off load
Gain adjustment	Clockwise to increase
Supply range	6-34V +DC. 1.2mA @ 12V, 3.5mA @ 24V
Supply configuration	Phantom supply or dedicated line

Note As the output level is relatively high, the corresponding amplifier input circuitry may be either:

- a line level input with integral phantom DC supply
- a line level input, with the unit powered from a separate 6-34V supply
- a microphone input preceded by a 60dB attenuator pad, with the unit powered from a 6-34V supply rail.

Use of the LPA.1 option directly with a phantom microphone input circuit will result in severe distortion.

All specifications are subject to change without notice in the interests of continuous improvement.



Electromagnetic compatibility (EMC) directive 89/336/EEC and amendment directive 92/31/EE. This equipment has been designed and manufactured to the highest standards. If connected and operated as set out in this manual, there should be no Electromagnetic Compatibility problems. If any aspect of operation gives rise to concern, then please contact the manufacturer for advice.