



# MUSTANG COMMUNICATIONS LTD

EASTFIELD INDUSTRIAL ESTATE, SCARBOROUGH, ENGLAND YO11 3UT

Telephone +44 (0) 1723 582555, FAX +44 (0) 1723 581673

[MP60-6] pm6 issue 2

## OPERATIONAL NOTES: MP.60S and MP.6S AUDIO MONITOR PANEL

### Application

Audible monitoring of 100V line signals by switch selection of amplifiers

### Specification

Capacity	6 channel selection by BBM switch
Channel isolation	1000V RMS minimum

#### MP.6S only:

Input	Nominally 100V. (Loudspeaker line level)
Line loading per channel	0.6W

#### MP.60S only:

Input	Nominally 0dB.
Line loading per channel	1k6 ohms
DC supply	24V @ 40mA quiescent, rising to 100mA on peaks of speech modulation. Internal F1A DC fuse.
Loudspeaker output	1 Watt maximum

### Adjustments

None

### Connections

Barrier terminals for 100V inputs (and for 24V DC supply input - MP.60S only).



Electromagnetic compatibility (EMC) directive 89/336/EEC and amendment directive 92/31/EE. This equipment has been designed and manufactured to the highest standards. If connected and operated as set out in this manual, there should be no Electromagnetic Compatibility problems. If any aspect of operation gives rise to concern, then please contact the manufacturer for advice.